



FEATURES

Metal case 250 x 160 x 100 mm
 INPUT : 85 - 265Vac
 OUTPUT : 300W
 Controlled by fully isolated RS232
 2 fully isolated outputs groups
 Programmable current fuses
 Measure of voltage and current
 Efficiency : 70 % typ.



APPLICATIONS

Automobile bench of test. Programmable laboratory PSU.

INPUT

Voltage range : 85 - 265Vac
 Nominal : 115 Vac or 230 Vac
 Input protection : fuse 4A
 transient and surges protected

OUTPUT

Dual fully isolated outputs with RS232 control for current and voltage

Output A : Programmable voltage from 6 to 29 Vdc
 Programmable current fuse from 0,1 to 3A
 Output B : 3 separate switchable outputs (programmable by RS232)
 Programmable voltage from 6 to 15 Vdc
 Programmable current fuse from 0,1 to 10A

	OUTPUT			Conditions
	Typ.	MAX.		
		A	B	
Line regulation	0,02 %	0,2 %		Low line to high line ; full load
Load regulation	0,02 %	0,5 %		No load to full load
Ripple and noise	1 %	2 %		Peak to peak, nom. Input ; full load
Current limit (current fuse type)	Programmable by RS232 from 0,1 to 3A	3A	10A	Output shut down RS232 command or pushbutton restart
Short circuit current		3A	10A	RS232 command or pushbutton restart

MEASURING SECTION

OUTPUT A

Voltage : 2 ADC 16 bits, 30V full scale
Current : 2 ADC 16 bits, 3A full scale

OUTPUT B

2ADC 16 bits, 15V full scale
2ADC 16 bits, 10A full scale

SIGNALS

Overcurrent indication : Open collector output + led

ENVIRONMENTAL

Storage temperature : -20°C to +85°C
Operating temperature : -10°C to +50°C ambient, nominal power

ISOLATION

Input to Chassis : 1500 Vrms or 2121 Vdc
Input to Output : 3000 Vrms or 4242 Vdc
Output to Chassis : >100 Mohms at 500 Vdc

GENERAL

Safety : built to meet EN60950
EMI : built to meet EN55022B, conducted.

MECHANICALS

FRONT PANEL OUTPUTS : 4mm terminals

	DESCRIPTION
+Vout A	1 red terminal
-Vout A	1 black terminal
+Vout B1	1 red terminal
+Vout B2	1 red terminal
+Vout B3	1 red terminal
-Vout B1, B2, B2	1 black terminal
Ground	1 yellow terminal



REAR PANEL INPUT CONNECTOR : CEE22 AC socket



Outputs, Sense Inputs and overcurrent open collector outputs in rear panel

REAR PANEL RS232 connector : SubD 9pts female

PIN	DESCRIPTION
1	NC
2	TxD
3	RxD
4	DTR
5	Ground
6	DTR
7, 8, 9	NC